

Connect 4G stick to the corresponding interface on the inverter. Solis-1P5K-4G is used as an example in this manual. Please perform relevant operations as indicated below:





Data Logger 4G Stick Interface

The device must be kept away from strong magnetic

fields generated by large electrical devices, such as

microwave ovens, refrigerators, wireless phones,

may also be affected by lightning.

photovoltaic panels and metal walls, to ensure the

quality of communication. The quality of communication

Data Logger 4G Stick Installation

1. Insert 4G Stick to COM port.

2. Fasten the 4G Stick.

NOTES

DLS Version: 1.2



Data Logger 4G Stick

Quick User Guide

■ 1 pc 4G Stick

Electrical Connection





Solis Pro

Step 2: Click on the "Register".




Step 3: Fill in the form as required and click



Create Solis monitoring account

Step 1: Mobile phone scan the QR code to download the APP, or in the APP Store or Google Play search Solis Home or Solis Pro.





3 Create plant

Step 1: In the APP homepage and click "Build Your

Plant Within 1 Minute!" in the middle of the screen.

Plant

atl 46 🔳

Or click the "+" in the upper right corner.

The datalogger SN can be automatically scanned by placing the purchased device bar code in the scan box. If you can't scan, you can also manually enter the datalogger SN (just enter the digital serial number)



Note: Please scan the SN number on the datalogger. not the SN number on the inverter.



Step 3: Enter the plant information. Then click the



Step 4: Enter the plant name and contact information of the plant owner. Then click the "Done".



4 Distrubutor/Installer create plant


In order to easy registration and easy manage, you can also let the distributor/installer register the plant. then Link it to you.

Click the [1] and tell the "ID" to your Distrubutor/installer to build the plant for you. (Note: your Distrubutor/installer must have a Solis Pro account)



5Link distributor/installer

Step 1: In order to easy manage to your plant. Select the plant and enter Intro. Click the "installer" or "distributor"



Step 2: Enter the company name of the installer or distributor. Then click the "Search"



Step 3: Click the [Bind Distributor/Installer] and the

plant will appear in your installer/distributor monitoring interface.

(Note: your installer/distributor must have a Solis Pro account to appear in the search list)



If you have any technical questions about our products, please contact us. Before contacting us, please confirm the following items:

- · Equipment model
- . Serial number of the datalogger
- · Problem description
- Screenshot of the Status page in the configuration interface

Ginlong Technologies Co., Ltd

No. 57 Jintong Road, Binhai Industrial Park. Xiangshan, Ningbo, Zhejiang, 315712, P.R.China.

Tel: +86 (0)574 6578 1806

Fax: +86 (0)574 6578 1606 Email: info@ginlong.com

Web: www.ginlong.com



1 pc 4G external antenna

■ 1 pc Data Logger 4G Stick Quick User Guide